



## MODEL NUMBER

**BX-23**

## SPECIFICATIONS

### FREQUENCY

868 MHz / 433 MHz

### POWER

1.5V, D Alkaline batteries x 4

### OPTIONAL POWER SOURCE

9V, 1A AC adaptor

### BATTERY LIFE

4.9years\*

\* Note: Actual battery life may vary with product settings, operating environment, and usage.

### SIREN OUTPUT

107dB at 1 meter

### STROBE LIGHT COVER

Blue (other colors available upon request)

### OPERATING TEMPERATURE

-25°C to 60°C (-13°F to 140°F)

### OPERATING HUMIDITY

Up to 85% non-condensing

### DIMENSIONS

205mm x 83mm x 317mm

### INGRESS PROTECTION

IP56

### CERTIFICATIONS

CE, EN Grade 2, RCM



## Outdoor Bell Box

- Wireless encrypted F1 Technology with 2km range
- Randomized supervision signals for system integrity checks and troubleshooting
- Tamper protection to prevent unauthorized removal, sabotage or unsteady installation
- Siren output level is 107dB at 1 meter
- Four programmable siren duration options and volume levels
- Programmable strobe activation
- Unique alarm sounds for fire and burglary
- Battery-operated or AC-powered
- Low battery detection and status
- Two-way communication with the control panel

## DESCRIPTION

The BX-23 bell box is a wireless, bi-directional outdoor sounder generating loud 107-decibel siren sounds and strobe lights during an alarm to provide visible and audible alerts. The bell box can either be powered by an AC adaptor or battery-operated. The BX-23 also provides a tamper-deterrent feature to protect against unauthorized removal or sabotage.

## SERVICE PACKAGES

- Commercial
- Commercial Plus
- Interactive
- Interactive + Automation
- Interactive Gold